

## Pin assignment

Pin assignment number: 10197

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 26

Page: 1/1

Pin	Designation	Description	Colour
1	O_D0	Data output	white
2	O_D1	Data output	brown
3	O_D2	Data output	green
4	O_D3	Data output	yellow
5	O_D4	Data output	gray
6	O_D5	Data output	pink
7	O_D6	Data output	blue
8	O_D7	Data output	red
9	O_D0 neg.	Data output inverted	black
10	O_D1 neg.	Data output inverted	violet
11	O_D2 neg.	Data output inverted	gray/pink
12	O_D3 neg.	Data output inverted	red/blue
13	O_D4 neg.	Data output inverted	white/green
14	O_D5 neg.	Data output inverted	brown/green
15	O_D6 neg.	Data output inverted	white/yellow
16	O_D7 neg.	Data output inverted	yellow/brown
17	not connected		
18	not connected		
19	not connected		
20	not connected		
21	Direction IN	Change of counting direction	white/blue
22	Ser.Program+_IN/OUT	Ser. programming interface RS485	brown/blue
23	Ser.Program-_IN/OUT	Ser. programming interface RS485	white/red
24	Supply Voltage IN	Supply voltage	brown/red
25	Ground IN	Ground	white/black
26	Preset1_IN	Preset value 1	brown/black

### WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.