

Pin assignment

Pin assignment number: 1072

Index:

13.01.2021

Connector name: 37-pol SUB-D

Pin-count: 37

Page: 1/2

Pin	Designation	Description	Colour
1	Ground IN	Ground	-
2	O_D0	Data output	-
3	O_D2	Data output	-
4	O_D4	Data output	-
5	O_D6	Data output	-
6	O_D8	Data output	-
7	O_D10	Data output	-
8	O_D12	Data output	-
9	O_D14	Data output	-
10	Direction IN	Change of counting direction	-
11	Parity_Odd_OUT	Parity Odd	-
12	DataBus_disable_IN	High=tristate	-
13	Supply Voltage IN	Supply voltage	-
14	not connected		-
15	not connected		-
16	not connected		-
17	not connected		-
18	not connected		-
19	not connected		-
20	not connected		-
21	O_D1	Data output	-
22	O_D3	Data output	-
23	O_D5	Data output	-
24	O_D7	Data output	-
25	O_D9	Data output	-
26	O_D11	Data output	-
27	O_D13	Data output	-
28	O_D15	Data output	-
29	not connected		-
30	I_Latch	High=Data enable	-
31	not connected		-
32	not connected		-
33	not connected		-
34	Ser.Program+_IN/OUT	Ser. programming interface RS485	-
35	Ser.Program-_IN/OUT	Ser. programming interface RS485	-
36	not connected		-
37	not connected		-

Pin assignment

Pin assignment number: 1072

Connector name: 37-pol SUB-D

Index:

Pin-count: 37

13.01.2021

Page: 2/2

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.