

## Pin assignment

Pin assignment number: 3608

Index: A

13.01.2021

Connector name: 26-pol SUB-D

Pin-count: 26

Page: 1/1

Pin	Designation	Description	Colour
1	Preset1_IN	Preset value 1	-
2	Ser.Program-_IN/OUT	Ser. programming interface RS485	-
3	Ser.Program+_IN/OUT	Ser. programming interface RS485	-
4	not connected		-
5	not connected		-
6	not connected		-
7	O_D0	Data output	-
8	/CH_A_OUT	Channel A inverted	-
9	CH_A_OUT	Channel A	-
10	not connected		-
11	Ground IN	Ground	-
12	not connected		-
13	not connected		-
14	not connected		-
15	not connected		-
16	ISI_Set_Done_OUT	Load End	-
17	not connected		-
18	not connected		-
19	Supply Voltage IN	Supply voltage	-
20	not connected		-
21	not connected		-
22	not connected		-
23	/CH_B_OUT	Channel B inverted	-
24	CH_B_OUT	Channel B	-
25	not connected		-
26	ISI_Set_IN	Load	-