

# Pin assignment

Pin assignment number: 3803

Connector name: with cable outlet

Index:

Pin-count: 10

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	PNT_Adress+_IN	Data input +	white
2	PNT_Adress-_IN	Data input -	brown
3	PNT_Data+_OUT	Data output +	green
4	PNT_Data-_OUT	Data output -	yellow
5	Baud 2 <sup>0</sup> _IN	Baud rate 2 <sup>0</sup>	gray
6	Baud 2 <sup>1</sup> _IN	Baud rate 2 <sup>1</sup>	pink
7	Preset1_IN	Preset value 1	blue
8	Preset2_IN	Preset value 2	red
9	Supply Voltage IN	Supply voltage	black
10	Ground IN	Ground	violet

<b>BAUD RATE :</b>	'	307200	38400	19200	9600
	2 <sup>0</sup> :	NC	US	NC	US
	2 <sup>1</sup> :	NC	NC	US	US
	2 <sup>2</sup> :	NC	NC	NC	NC
	2 <sup>3</sup> :	NC	NC	NC	NC
	'				

## WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.