

Pin assignment

Pin assignment number: 3951

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN	Clock input -	green
2	SSI_Clock+_IN	Clock input +	yellow
3	SSI_DATA+_OUT	Data output +	gray
4	SSI_DATA-_OUT	Data output -	pink
5	Ser.Program+_IN/OUT	Ser. programming interface RS485	blue
6	Ser.Program-_IN/OUT	Ser. programming interface RS485	red
7	CH_A_OUT	Channel A	black
8	/CH_A_OUT	Channel A inverted	violet
9	CH_B_OUT	Channel B	gray/pink
10	/CH_B_OUT	Channel B inverted	red/blue
11	Softendswitch_OUT1	Data output	white/green
12	Softendswitch_OUT2	Data output	brown/green
13	Softendswitch_OUT3	Data output	white/yellow
14	Supply Voltage IN	Supply voltage	white
15	Ground IN	Ground	brown

SCHIRM :

'Schirm vom Kabel (Litze: grün/gelb) an Lötöse M2,5 anlöten !!!

,

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.
,