

Pin assignment

Pin assignment number: 4094

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 37

Page: 1/2

Pin	Designation	Description	Colour
1	O_D0	Data output	white
2	O_D1	Data output	brown
3	O_D2	Data output	green
4	O_D3	Data output	yellow
5	O_D4	Data output	gray
6	O_D5	Data output	pink
7	O_D6	Data output	blue
8	O_D7	Data output	red
9	O_D8	Data output	black
10	O_D9	Data output	violet
11	O_D10	Data output	gray/pink
12	O_D11	Data output	red/blue
13	O_D12	Data output	white/green
14	O_D13	Data output	brown/green
15	O_D14	Data output	white/yellow
16	O_D15	Data output	yellow/brown
17	O_D16	Data output	white/gray
18	O_D17	Data output	gray/brown
19	not connected		
20	not connected		
21	not connected		
22	not connected		
23	not connected		
24	not connected		
25	SSI_Clock-_IN	Clock input -	white/black
26	SSI_Clock+_IN	Clock input +	brown/black
27	SSI_DATA+_OUT	Data output +	gray/green
28	SSI_DATA-_OUT	Data output -	yellow/gray
29	Direction IN	Change of counting direction	pink/green
30	not connected		
31	not connected		
32	Preset1_IN	Preset value 1	yellow/blue
33	Preset2_IN	Preset value 2	green/red
34	Ser.Program+_IN/OUT	Ser. programming interface RS485	yellow/red
35	Ser.Program-_IN/OUT	Ser. programming interface RS485	green/black
36	Supply Voltage IN	Supply voltage	yellow/black
37	Ground IN	Ground	gray/blue

Pin assignment

Pin assignment number: 4094

Connector name: with cable outlet

Index:

Pin-count: 37

13.01.2021

Page: 2/2

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.