

Pin assignment

Pin assignment number: 9726

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 18

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN	Clock input -	white
2	SSI_Clock+_IN	Clock input +	brown
3	SSI_DATA+_OUT	Data output +	green
4	SSI_DATA-_OUT	Data output -	yellow
5	CH_A_OUT	Channel A	gray
6	/CH_A_OUT	Channel A inverted	pink
7	CH_B_OUT	Channel B	blue
8	/CH_B_OUT	Channel B inverted	red
9	Ser.Program+_IN/OUT	Ser. programming interface RS485	black
10	Ser.Program-_IN/OUT	Ser. programming interface RS485	violet
11	Direction IN	Change of counting direction	gray/pink
12	Preset1_IN	Preset value 1	red/blue
13	Preset2_IN	Preset value 2	white/green
14	O_D0	Data output	brown/green
15	O_D1	Data output	white/yellow
16	Supply Voltage IN	Supply voltage	yellow/brown
17	Ground IN	Ground	white/gray
18	not connected		

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.