

# Pin assignment

Pin assignment number: 1371

Index: + 1694 = K116

13.07.2011

Connector name: 32-pol.CANNON Pin-count: 32

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A	O_D0	Data output				white
B	O_D1	Data output				brown
C	O_D2	Data output				green
D	O_D3	Data output				yellow
E	O_D4	Data output				gray
F	O_D5	Data output				pink
G	O_D6	Data output				blue
H	O_D7	Data output				red
J	O_D8	Data output				black
K	O_D9	Data output				violet
L	O_D10	Data output				gray/pink
M	O_D11	Data output				red/blue
N	O_D12	Data output				withe/green
P	O_D13	Data output				brown/green
R	O_D14	Data output				withe/yellow
S	O_D15	Data output				yellow/brown
T	O_D16	Data output				withe/gray
U	O_D17	Data output				gray/brown
V	not connected					
W	not connected					
X	Direction IN	Counting direction increasing	Supply Voltage		0	withe/blue
Y	Preset1_IN	Preset value 1	Supply Voltage		0	brown/blue
Z	not connected					
a	Supply Voltage IN	Supply voltage	11-27V			brown/red
b	Ground IN	Ground	0V			withe/black
c	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown/black
d	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		gray/green
e	not connected					
f	not connected					
g	not connected					
h	not connected					
i	not connected					

# Pin assignment

Pin assignment number: 1694

Index: + 1371 = K116

13.07.2011

Connector name: 32-pol.CANNON Pin-count: 32

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A	O_D0	Data output				white
B	O_D1	Data output				brown
C	O_D2	Data output				green
D	O_D3	Data output				yellow
E	O_D4	Data output				gray
F	O_D5	Data output				pink
G	O_D6	Data output				blue
H	O_D7	Data output				red
J	O_D8	Data output				black
K	O_D9	Data output				violet
L	O_D10	Data output				gray/pink
M	O_D11	Data output				red/blue
N	O_D12	Data output				withe/green
P	O_D13	Data output				brown/green
R	O_D14	Data output				withe/yellow
S	O_D15	Data output				yellow/brown
T	O_D16	Data output				withe/gray
U	O_D17	Data output				gray/brown
V	not connected					
W	not connected					
X	Direction IN	Counting direction increasing	Supply Voltage		0	withe/blue
Y	Preset1_IN	Preset value 1	Supply Voltage		0	brown/blue
Z	not connected					
a	Supply Voltage IN	Supply voltage	11-27V			brown/red
b	Ground IN	Ground	0V			withe/black
c	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown/black
d	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		gray/green
e	not connected					
f	not connected					
g	not connected					
h	not connected					
i	not connected					