

Pin assignment

Pin assignment number: 1698

Index: + 1699 = K118

13.07.2011

Connector name: 25-pol.SUB-D

Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	O_D0	Data output				white
2	O_D1	Data output				brown
3	O_D2	Data output				green
4	O_D3	Data output				yellow
5	O_D4	Data output				gray
6	O_D5	Data output				pink
7	O_D6	Data output				blue
8	O_D7	Data output				red
9	O_D8	Data output				black
10	O_D9	Data output				violet
11	not connected					
12	not connected					
13	Parity_Even_OUT	Parity Even				withe/green
14	not connected					
15	not connected					
16	not connected					
17	not connected					
18	not connected					
19	not connected					
20	not connected					
21	Direction IN	Change of counting direction	Supply Voltage		0	withe/blue
22	Supply Voltage IN	Supply voltage	11-27V			brown/blue
23	Ground IN	Ground	0V			withe/red
24	Supply Voltage IN	Supply voltage	11-27V			brown/red
25	Supply Voltage IN	Supply voltage	11-27V			withe/black

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 1699

Index: + 1698 = K118

13.07.2011

Connector name: 25-pol.HARTING Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A1	O_D0	Data output				white
A2	O_D1	Data output				brown
A3	O_D2	Data output				green
A4	O_D3	Data output				yellow
A5	O_D4	Data output				gray
A6	O_D5	Data output				pink
A7	O_D6	Data output				blue
A8	O_D7	Data output				red
A9	O_D8	Data output				black
B2	O_D9	Data output				violet
B3	not connected					
B4	not connected					
B5	Parity_Even_OUT	Parity Even				withe/green
B6	not connected					
B7	not connected					
B8	not connected					
C1	not connected					
C2	not connected					
C3	not connected					
C4	not connected					
C5	Direction IN	Change of counting direction	Supply Voltage		0	withe/blue
C6	Supply Voltage IN	Supply voltage	11-27V			brown/blue
C7	Ground IN	Ground	0V			withe/red
C8	Supply Voltage IN	Supply voltage	11-27V			brown/red
C9	Supply Voltage IN	Supply voltage	11-27V			withe/black

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.