

Pin assignment

Pin assignment number: 1927**Index:**

25.01.2013

Connector name: 9-pol. SUB-D**Pin-count: 9****+ 246 = K137**

Page: 1/1

| Pin | Designation | Description | Level | Driver | NC | Colour |
|-----|-------------------|----------------|--------|--------|----|--------|
| 1 | Supply Voltage IN | Supply voltage | 11-27V | | | red |
| 2 | not connected | | | | | |
| 3 | SOUT | | | | | white |
| 4 | SOI | | | | | brown |
| 5 | SIN | | | | | green |
| 6 | ERR | | | | | yellow |
| 7 | CYC | | | | | gray |
| 8 | Ground IN | Ground | 0V | | | pink |
| 9 | Level_OUT | Level voltage | 5V | | | blue |

Pin assignment

Pin assignment number: 246
Index:
 + 1927 = K137

25.01.2013

Connector name: 15-pol.SUB-D
Pin-count: 15

Page: 1/1

| Pin | Designation | Description | Level | Driver | NC | Colour |
|-----|---------------------|----------------------------------|--------|--------|----|--------------|
| 1 | Ser.Program-_IN/OUT | Ser. programming interface RS485 | RS 485 | RS 485 | | white |
| 2 | Ser.Program+_IN/OUT | Ser. programming interface RS485 | RS 485 | RS 485 | | brown |
| 3 | not connected | | | | | |
| 4 | not connected | | | | | |
| 5 | not connected | | | | | |
| 6 | not connected | | | | | |
| 7 | not connected | | | | | |
| 8 | not connected | | | | | |
| 9 | not connected | | | | | |
| 10 | not connected | | | | | |
| 11 | not connected | | | | | |
| 12 | not connected | | | | | |
| 13 | not connected | | | | | |
| 14 | Supply Voltage IN | Supply voltage | 11-27V | | | brown/green |
| 15 | Ground IN | Ground | 0V | | | white/yellow |

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.