

Pin assignment

Pin assignment number: 2679

Index: +246 = K200

26.07.2011

Connector name: 12-pol.CONTACT Pin-count: 12

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	CH_A_OUT	Channel A	RS 422	RS 422		white
2	/CH_A_OUT	Channel A inverted	RS 422	RS 422		brown
3	CH_B_OUT	Channel B	RS 422	RS 422		green
4	/CH_B_OUT	Channel B inverted	RS 422	RS 422		yellow
5	not connected					
6	not connected					
7	ISI_Set_IN	Load	Supply Voltage	Push Pull		blue
8	ISI_Set_Done_OUT	Load End	Supply Voltage	Push Pull		red
9	Preset1_IN	Preset value 1	Supply Voltage		0	black
10	Preset2_IN	Preset value 2	Supply Voltage		0	violet
11	Supply Voltage IN	Supply voltage	11-27V			gray/pink
12	Ground IN	Ground	0V			red/blue

Pin assignment

Pin assignment number: 246

Index: + 2679 = K200

11.07.2011

Connector name: 15-pol.SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	Adress 2 ⁰ _IN	Encoder address 2 ⁰	Supply Voltage		0	white
2	Adress 2 ¹ _IN	Encoder address 2 ¹	Supply Voltage		0	brown
3	Adress 2 ² _IN	Encoder address 2 ²	Supply Voltage		0	green
4	Adress 2 ³ _IN	Encoder address 2 ³	Supply Voltage		0	yellow
5	not connected					
6	DATA+_OUT	Data output +	RS 422	RS 422		pink
7	DATA-_OUT	Data output -	RS 422	RS 422		blue
8	Clock+_ IN	Clock input +	RS 422	RS 422		red
9	Clock-_ IN	Clock input -	RS 422	RS 422		black
10	not connected					
11	not connected					
12	Format recognition					red/blue
13	not connected					
14	Supply Voltage IN	Supply voltage	11-27V			brown/green
15	Ground IN	Data output	0V			withe/yellow

FORMAT DETECTION:

'LOW = TA-MINI

HIGH = PT-100

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.