

Pin assignment

Pin assignment number: 3385

Index: A + 3391 = K270

01.09.2011

Connector name: 12-pol.CONTACT Pin-count: 12

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	Ground IN	Ground	0V			white
2	SSI_DATA+_OUT	Data output +	RS 422	RS 422		brown
3	SSI_Clock+_IN	Clock input +	RS 422	RS 422		green
4	not connected					
5	Direction IN	Change of counting direction	Supply Voltage		0	gray
6	not connected					
7	Preset1_IN	Preset value 1	Supply Voltage		0	blue
8	Supply Voltage IN	Supply voltage	11-27V			red
9	not connected					
10	SSI_DATA-_OUT	Data output -	RS 422	RS 422		violet
11	SSI_Clock-_IN	Clock input -	RS 422	RS 422		gray/pink
12	not connected					

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 3391
Index: + 3385A = K270

01.09.2011

Connector name: 12-pol.TUCHEL Pin-count: 12

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A	Supply Voltage IN	Supply voltage	11-27V			white
B	Ground IN	Ground	0V			brown
C	not connected					
D	not connected					
E	CH_A_OUT	Channel A	11-27V	Push Pull		gray
F	not connected					
G	CH_B_OUT	Channel B	11-27V	Push Pull		blue
H	not connected					
J	/CH_A_OUT	Channel A inverted	11-27V	Push Pull		black
K	/CH_B_OUT	Channel B inverted	11-27V	Push Pull		violet
L	CH_I_OUT	Channel Reference	11-27V	Push Pull		gray/pink
M	/CH_I_OUT	Channel Reference inverted	11-27V	Push Pull		red/blue

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.