

Pin assignment

Pin assignment number: 3801

Index: + 3802 = K323

13.09.2011

Connector name: 25-pol.SUB-D

Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	not connected					
2	not connected					
3	not connected					
4	not connected					
5	not connected					
6	not connected					
7	not connected					
8	not connected					
9	not connected					
10	not connected					
11	not connected					
12	not connected					
13	Analog +	Analog output	0..5V			white/green
14	not connected					
15	not connected					
16	not connected					
17	SSI_Clock-_IN	Clock input -	RS 422	RS 422		white/gray
18	SSI_Clock+_IN	Clock input +	RS 422	RS 422		gray/brown
19	SSI_DATA+_OUT	Data output +	RS 422	RS 422		white/pink
20	SSI_DATA-_OUT	Data output -	RS 422	RS 422		pink/brown
21	not connected					
22	Supply Voltage IN	Supply voltage	18-27V			brown/blue
23	Supply Voltage IN	Supply voltage	18-27V			white/red
24	Ground IN	Ground	0V			brown/red
25	Ground IN	Ground	0V			white/black

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 3802

Index: + 3801 = K323

13.09.2011

Connector name: 15-pol.SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		white
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown
3	not connected					
4	not connected					
5	not connected					
6	not connected					
7	not connected					
8	not connected					
9	Preset1_IN	Preset value 1	Supply Voltage		0	black
10	not connected					
11	not connected					
12	not connected					
13	not connected					
14	Supply Voltage IN	Supply voltage	18-27V			brown/green
15	Ground IN	Data output	0V			white/yellow

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.