

# Pin assignment

Pin assignment number: 3822

Index: + 246 = K332

13.09.2011

Connector name: with cable outlet Pin-count:

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	CH_A_OUT	Channel A	11-27V	Push Pull		green
2	/CH_A_OUT	Channel A inverted	11-27V	Push Pull		pink
3	CH_B_OUT	Channel B	11-27V	Push Pull		yellow
4	/CH_B_OUT	Channel B inverted	11-27V	Push Pull		blue
5	CH_I_OUT	Channel Reference	11-27V	Push Pull		red
6	/CH_I_OUT	Channel Reference inverted	11-27V	Push Pull		gray
7	Supply Voltage IN	Supply voltage	11-27V			brown
8	Ground IN	Ground	0V			white

**WARNING !!**

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!  
Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

# Pin assignment

Pin assignment number: 246

Index: + 3822 = K332

31.08.2011

Connector name: 15-pol.SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		white
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown
3	not connected					
4	not connected					
5	not connected					
6	not connected					
7	not connected					
8	not connected					
9	not connected					
10	not connected					
11	not connected					
12	not connected					
13	not connected					
14	Supply Voltage IN	Supply voltage	11-27V			brown/green
15	Ground IN	Ground	0V			withe/yellow

**WARNING !!**

**'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!**

**Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.**

**Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.**