

# Pin assignment

Pin assignment number: 3152

Index: + 1345B = K355

15.09.2011

Connector name: 12-pol.CONTACT

Pin-count: 12

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	SSI_Clock-_IN	Clock input -	RS 422	RS 422		white
2	SSI_Clock+_IN	Clock input +	RS 422	RS 422		brown
3	SSI_DATA+_OUT	Data output +	RS 422	RS 422		green
4	SSI_DATA-_OUT	Data output -	RS 422	RS 422		yellow
5	not connected					
6	not connected					
7	not connected					
8	Direction IN	Change of counting direction	Supply Voltage		0	red
9	not connected					
10	not connected					
11	Supply Voltage IN	Supply voltage	11-27V			gray/pink
12	Ground IN	Ground	0V			red/blue

**WARNING !!**

**'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!**

**Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.**

**Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.**

# Pin assignment

**Pin assignment number: 1345**
**Index: B + 3152 = K355**

15.09.2011

**Connector name: 12-pol.CONTACT**
**Pin-count: 12**

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	CH_A_OUT	Channel A	5V	RS 422		yellow
2	/CH_A_OUT	Channel A inverted	5V	RS 422		violet
3	not connected					
4	CH_B_OUT	Channel B	5V	RS 422		pink
5	/CH_B_OUT	Channel B inverted	5V	RS 422		white
6	not connected					
7	CH_I_OUT	Channel Reference	5V	RS 422		green
8	/CH_I_OUT	Channel Reference inverted	5V	RS 422		brown
9	not connected					
10	not connected					
11	Supply Voltage IN	Supply voltage	11-27V			red
12	Ground IN	Ground	0V			blue

**WARNING !!**

**'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!**

**Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.**

**Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.**