

Pin assignment

Pin assignment number: 2130

Index: A + 246 = K370

16.09.2011

Connector name: 25-pol.SUB-D

Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Colour
1	O_D0	Data output				gray/brown
2	O_D1	Data output				white/red
3	O_D2	Data output				white/gray
4	O_D3	Data output				pink/brown
5	O_D4	Data output				white/yellow
6	O_D5	Data output				white/pink
7	O_D6	Data output				yellow
8	O_D7	Data output				yellow/brown
9	O_D8	Data output				pink
10	O_D9	Data output				brown/red
11	O_D10	Data output				gray
12	O_D11	Data output				brown
13	O_D12	Data output				brown/blue
14	O_D13	Data output				white/blue
15	O_D14	Data output				gray/pink
16	O_D15	Data output				blue
17	O_D16	Data output				violet
18	O_D17	Data output				green
19	O_D18	Data output				red/blue
20	Up_Down_OUT	Downward movement	Supply Voltage			pink/brown
21	I_Latch	High=Latch	Supply Voltage		0	white
22	Preset1_IN	Preset value 1	Supply Voltage		0	brown/green
23	Supply Voltage IN	Supply voltage 11-27V	11-27V			red
24	Ground IN	Ground	0V			black
25	Ground IN	Ground	0V			white/black

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 246

Index: + 2130A = K370

31.08.2011

Connector name: 15-pol.SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		white
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown
3	not connected					
4	not connected					
5	not connected					
6	not connected					
7	not connected					
8	not connected					
9	not connected					
10	not connected					
11	not connected					
12	not connected					
13	not connected					
14	Supply Voltage IN	Supply voltage	11-27V			brown/green
15	Ground IN	Ground	0V			withe/yellow

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.