

Pin assignment

Pin assignment number: 1345

Index:

10.10.2012

+ 1876 = K422

Connector name: 12-pol.CONTACT

Pin-count: 12

Page: 1/1

| Pin | Designation | Description | Level | Driver | NC | Colour |
|-----|-------------------|----------------------------|--------|--------|----|--------|
| 1 | CH_A_OUT | Channel A | 5V | RS 422 | | yellow |
| 2 | /CH_A_OUT | Channel A inverted | 5V | RS 422 | | violet |
| 3 | not connected | | | | | |
| 4 | CH_B_OUT | Channel B | 5V | RS 422 | | pink |
| 5 | /CH_B_OUT | Channel B inverted | 5V | RS 422 | | white |
| 6 | not connected | | | | | |
| 7 | CH_I_OUT | Channel Reference | 5V | RS 422 | | green |
| 8 | /CH_I_OUT | Channel Reference inverted | 5V | RS 422 | | brown |
| 9 | not connected | | | | | |
| 10 | not connected | | | | | |
| 11 | Supply Voltage IN | Supply voltage | 11-27V | | | red |
| 12 | Ground IN | Ground | 0V | | | blue |

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 1876

Index: + 1345 = K422

10.10.2012

Connector name: 12-pol.CONTACT

Pin-count: 12

Page: 1/1

| Pin | Designation | Description | Level | Driver | NC | Colour |
|-----|-------------------|----------------------------|--------|-----------|----|--------|
| 1 | CH_A_OUT | Channel A | 11-27V | Push Pull | | yellow |
| 2 | /CH_A_OUT | Channel A inverted | 11-27V | Push Pull | | violet |
| 3 | not connected | | | | | |
| 4 | CH_B_OUT | Channel B | 11-27V | Push Pull | | pink |
| 5 | /CH_B_OUT | Channel B inverted | 11-27V | Push Pull | | white |
| 6 | not connected | | | | | |
| 7 | CH_I_OUT | Channel Reference | 11-27V | Push Pull | | green |
| 8 | /CH_I_OUT | Channel Reference inverted | 11-27V | Push Pull | | brown |
| 9 | not connected | | | | | |
| 10 | not connected | | | | | |
| 11 | Supply Voltage IN | Supply voltage | 11-27V | | | red |
| 12 | Ground IN | Ground | 0V | | | blue |

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.