

# Pin assignment

Pin assignment number: 1298

Index: + 1299 = K98

12.07.2011

Connector name: 25-pol.HARTING Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A1	O_D0	Data output				brown
A2	O_D1	Data output				green
A3	O_D2	Data output				white
A4	O_D3	Data output				pink
A5	O_D4	Data output				yellow
A6	O_D5	Data output				black
A7	O_D6	Data output				gray
A8	O_D7	Data output				brown/blue
A9	O_D8	Data output				brown/gray
B2	O_D9	Data output				yellow/brown
B3	O_D10	Data output				red/blue
B4	O_D11	Data output				withe/yellow
B5	O_D12	Data output				withe/red
B6	O_D13	Data output				violet
B7	O_D14	Data output				withe/gray
B8	O_D15	Data output				brown/green
C1	not connected					
C2	Parity	Parity Even				gray/pink
C3	not connected					
C4	not connected					
C5	Screen	Shield				
C6	Preset1_IN	Supply voltage	Supply Voltage		0	withe/blue
C7	not connected					
C8	Supply Voltage IN	Supply voltage	11-27V			red
C9	Ground IN	Ground	0V			blue

**WARNING !!**

**'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!**

**Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.**

**Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.**

# Pin assignment

Pin assignment number: 1299

Index: + 1298 = K98

12.07.2011

Connector name: 15-pol.SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	Ser.Program-_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		white
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	RS 485	RS 485		brown
3	not connected					
4	not connected					
5	not connected					
6	not connected					
7	not connected					
8	not connected					
9	not connected					
10	not connected					
11	not connected					
12	not connected					
13	not connected					
14	Supply Voltage IN	Supply voltage	11-27V			brown/green
15	Ground IN	Data output	0V			withe/yellow

**WARNING !!**

**'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!**

**Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.**

**Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.**