

# Pin assignment

Pin assignment number: 10220

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 16

Page: 1/1

| Pin | Designation         | Description                      | Colour       |
|-----|---------------------|----------------------------------|--------------|
| 1   | SSI_Clock-_IN       | Clock input -                    | green/white  |
| 2   | SSI_Clock+_IN       | Clock input +                    | white/orange |
| 3   | SSI_DATA+_OUT       | Data output +                    | green        |
| 4   | SSI_DATA-_OUT       | Data output -                    | orange       |
| 5   | Ser.Program+_IN/OUT | Ser. programming interface RS485 | white        |
| 6   | Ser.Program-_IN/OUT | Ser. programming interface RS485 | brown        |
| 7   | not connected       |                                  |              |
| 8   | Direction IN        | Change of counting direction     | blue         |
| 9   | Preset1_IN          | Preset value 1                   | yellow       |
| 10  | not connected       |                                  |              |
| 11  | not connected       |                                  |              |
| 12  | not connected       |                                  |              |
| 13  | not connected       |                                  |              |
| 14  | not connected       |                                  |              |
| 15  | Supply Voltage IN   | Supply voltage                   | red          |
| 16  | Ground IN           | Ground                           | black        |

## SCHIRM :

'Schirm vom Kabel (Litze: grün/gelb) an Lötöse M2,5 anlöten !!!

\*\*\*\*\*  
,

## WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.