

Pin assignment

Pin assignment number: 10013

Index:

13.01.2021

Connector name: M23 12-pol

Pin-count: 12

Page: 1/1

Pin	Designation	Description	Colour
1	/CH_B_OUT	Channel B inverted	-
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	-
3	CH_I_OUT	Channel Reference	-
4	/CH_I_OUT	Channel Reference inverted	-
5	CH_A_OUT	Channel A	-
6	/CH_A_OUT	Channel A inverted	-
7	Ser.Program-_IN/OUT	Ser. programming interface RS485	-
8	CH_B_OUT	Channel B	-
9	Screen	Shield	-
10	Ground IN	Ground	-
11	Ground IN	Ground	-
12	Supply Voltage IN	Supply voltage	-