

Pin assignment

Pin assignment number: 10209

Index:

13.01.2021

Connector name: with cable outlet

Pin-count: 12

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN	Clock input -	green
2	SSI_Clock+_IN	Clock input +	yellow
3	SSI_DATA+_OUT	Data output +	gray
4	SSI_DATA-_OUT	Data output -	pink
5	Ser.Program+_IN/OUT	Ser. programming interface RS485	blue
6	Ser.Program-_IN/OUT	Ser. programming interface RS485	red
7	Direction IN	Change of counting direction	black
8	Preset IN	Preset value 1	violet
9	Heating_IN	Heating +24V	white 0,5
10	Heating Ground_IN	Heating Ground	brown 0,5
11	Supply Voltage IN	Supply voltage	white
12	Ground IN	Ground	brown

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.