

## Pin assignment

Pin assignment number: 10815

Connector name: with cable outlet

Index:

Pin-count: 18

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN	Clock input -	white
2	SSI_Clock+_IN	Clock input +	brown
3	SSI_DATA+_OUT	Data output +	green
4	SSI_DATA-_OUT	Data output -	yellow
5	CH_A_OUT	Channel A	gray
6	/CH_A_OUT	Channel A inverted	pink
7	CH_B_OUT	Channel B	blue
8	/CH_B_OUT	Channel B inverted	red
9	Ser.Program+_IN/OUT	Channel B	black
10	Ser.Program-_IN/OUT	Channel B inverted	violet
11	Supply Voltage IN	Supply voltage	gray/pink
12	Ground IN	Ground	red/blue
13	not connected		
14	not connected		
15	not connected		
16	not connected		
17	not connected		
18	not connected		

### WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.