

Pin assignment

Pin assignment number: 1356

Connector name: 8-pol HARTING

Index:

Pin-count: 8

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	PNT_Adress+_IN	Data input +	-
2	PNT_Adress-_IN	Data input -	-
3	PNT_Data+_OUT	Data output +	-
4	PNT_Data-_OUT	Data output -	-
5	Baud 2 ⁰ _IN	Baud rate 2 ⁰	-
6	Baud 2 ¹ _IN	Baud rate 2 ¹	-
7	Supply Voltage IN	Supply voltage	-
8	Ground IN	Ground	-

BAUD RATE :	'	307200	38400	19200	9600
2 ⁰ :	NC	US	NC	US	
2 ¹ :	NC	NC	US	US	
2 ² :	NC	NC	NC	NC	
2 ³ :	NC	NC	NC	NC	
'					

Switching PENET/HAS : 'Switch position of the DIP-Switch

2 ⁰	2 ¹	2 ²	2 ³	2 ⁴	2 ⁵	Address	Operation Mode
S1	S2	S3	S4	S5	S6		
OFF	OFF	OFF	OFF	OFF	OFF	Soft Addr.	PENET
ON	OFF	OFF	OFF	OFF	OFF	1	PENET
OFF	ON	OFF	OFF	OFF	OFF	2	PENET
ON	ON	OFF	OFF	OFF	OFF	3	PENET
.	.	.	.	.	.	.	.
ON	ON	ON	ON	ON	OFF	31	PENET
X	X	X	X	X	ON	X	HAS
'							