

Pin assignment

Pin assignment number: 1650

Connector name: M23 12-pol

Index: A

Pin-count: 12

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	PNT_Adress+_IN	Data input +	-
2	PNT_Adress-_IN	Data input -	-
3	PNT_Data+_OUT	Data output +	-
4	PNT_Data-_OUT	Data output -	-
5	Baud 2 ⁰ _IN	Baud rate 2 ⁰	-
6	Baud 2 ¹ _IN	Baud rate 2 ¹	-
7	Adress 2 ⁰ _IN	Encoder address 2 ⁰	-
8	Adress 2 ¹ _IN	Encoder address 2 ¹	-
9	Adress 2 ² _IN	Encoder address 2 ²	-
10	Preset1_IN	Preset value 1	-
11	Supply Voltage IN	Supply voltage	-
12	Ground IN	Ground	-

BAUD RATE :	'	307200	38400	19200	9600
	2 ⁰ :	NC	US	NC	US
	2 ¹ :	NC	NC	US	US
	2 ² :	NC	NC	NC	NC
	2 ³ :	NC	NC	NC	NC
	'				