

## Pin assignment

Pin assignment number: 1881

Connector name: with cable outlet

Index:

Pin-count: 25

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN	Clock input -	white
2	SSI_Clock+_IN	Clock input +	brown
3	SSI_DATA+_OUT	Data output +	green
4	SSI_DATA-_OUT	Data output -	yellow
5	not connected		
6	not connected		
7	not connected		
8	Direction IN	Change of counting direction	gray
9	Preset1_IN	Preset value 1	pink
10	not connected		
11	not connected		
12	not connected		
13	not connected		
14	not connected		
15	not connected		
16	not connected		
17	not connected		
18	not connected		
19	not connected		
20	not connected		
21	not connected		
22	not connected		
23	not connected		
24	Supply Voltage IN	Supply voltage	red
25	Ground IN	Ground	blue

### WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.