

## Pin assignment

Pin assignment number: 2804

Index:

13.01.2021

Connector name: 15-pol SUB-D

Pin-count: 15

Page: 1/1

Pin	Designation	Description	Colour
1	Ser.Program-_IN/OUT	Ser. programming interface RS485	-
2	Ser.Program+_IN/OUT	Ser. programming interface RS485	-
3	CH_A_OUT	Channel A	-
4	/CH_A_OUT	Channel A inverted	-
5	CH_B_OUT	Channel B	-
6	/CH_B_OUT	Channel B inverted	-
7	not connected		-
8	not connected		-
9	CH_I_OUT	Channel Reference	-
10	/CH_I_OUT	Channel Reference inverted	-
11	not connected		-
12	not connected		-
13	not connected		-
14	Supply Voltage IN	Supply voltage	-
15	Ground IN	Ground	-