

## Pin assignment

Pin assignment number: 3047

Connector name: M23 12-pol

Index:

Pin-count: 12

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	not connected		-
2	CAN L		-
3	CAN GND		-
4	BAUD	Baud rate 1MB	-
5	Ground IN	Ground	-
6	BAUD	Baud rate 125KB	-
7	CAN H		-
8	not connected		-
9	not connected		-
10	Ground IN	Ground	-
11	not connected		-
12	Supply Voltage IN	Supply voltage	-

### Baud rate-Selection

'Unconnected = 500 KB

PIN4 connected to PIN5 = 1 MB

PIN6 connected to PIN5 = 125 KB

### WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.