

Pin assignment

Pin assignment number: 3185

Connector name: with cable outlet

Index: A

Pin-count: 18

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	O_D0	Data output	white
2	O_D1	Data output	yellow
3	O_D2	Data output	green
4	O_D3	Data output	gray
5	O_D4	Data output	pink
6	O_D5	Data output	brown
7	O_D6	Data output	black
8	O_D7	Data output	red/blue
9	O_D8	Data output	gray/pink
10	not connected		
11	Direction IN	Change of counting direction	violet
12	not connected		
13	not connected		
14	not connected		
15	not connected		
16	not connected		
17	Supply Voltage IN	Supply voltage	red
18	Ground IN	Ground	blue

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.