

Pin assignment

Pin assignment number: 3695

Index:

13.01.2021

Connector name: M23 12-pol

Pin-count: 12

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock+_IN	Clock input +	-
2	SSI_DATA+_OUT	Data output +	-
3	Ser.Program+_IN/OUT	Ser. programming interface RS485	-
4	Ser.Program-_IN/OUT	Ser. programming interface RS485	-
5	Direction IN	Change of counting direction	-
6	not connected		-
7	SSI_Clock-_IN	Clock input -	-
8	not connected		-
9	not connected		-
10	SSI_DATA-_OUT	Data output -	-
11	Supply Voltage IN	Supply voltage	-
12	Ground IN	Ground	-

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.