

## Pin assignment

Pin assignment number: 64

Connector name: 10-pol AMPHENOL

Index:

Pin-count: 10

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
A	SSI_DATA-_OUT	Data output -	-
B	SSI_DATA+_OUT	Data output +	-
C	Direction IN	Change of counting direction	-
D	Preset1_IN	Preset value 1	-
E	Preset2_IN	Preset value 2	-
F	Con_Check	Connector monitoring	-
G	SSI_Clock-_IN	Clock input -	-
H	SSI_Clock+_IN	Clock input +	-
I	Supply Voltage IN	Supply voltage	-
J	Ground IN	Ground	-

### WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.