

Pin assignment

Pin assignment number: 9784

Connector name: with cable outlet

Index:

Pin-count: 25

13.01.2021

Page: 1/1

Pin	Designation	Description	Colour
1	SSI_Clock-_IN 1	Clock input -	red
2	SSI_Clock+_IN 1	Clock input +	blue
3	SSI_DATA+/Prg.+_1	Data+/Prog.-Input+	green
4	SSI_DATA-/Prg.-_1	Data-/Prog.-Input-	yellow
5	not connected		
6	not connected		
7	not connected		
8	Direction IN_1	Change of counting direction	gray
9	Preset1 IN_1	Preset value 1	pink
10	not connected		
11	Supply Voltage IN_1	Supply voltage	white
12	Ground IN_1	Ground	brown
13	-		
14	SSI_Clock-_IN 2	Clock input -	red
15	SSI_Clock+_IN 2	Clock input +	blue
16	SSI_DATA+/Prg.+_2	Data+/Prog.-Input+	green
17	SSI_DATA-/Prg.-_2	Data-/Prog.-Input-	yellow
18	not connected		
19	not connected		
20	not connected		
21	Direction IN_2	Change of counting direction	gray
22	Preset1 IN_2	Preset value 1	pink
23	not connected		
24	Supply Voltage IN_2	Supply voltage	white
25	Ground IN_2	Ground	brown

WARNING

'De-energize the system before carrying out wiring work or opening and closing electrical connections !

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen ! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.