

Pin assignment

Pin assignment number: 2050

Index: + 1074 = K140

20.07.2011

Connector name: 25-pol.SUB-D

Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	O_D0	Data output				white
2	O_D1	Data output				brown
3	O_D2	Data output				green
4	O_D3	Data output				yellow
5	O_D4	Data output				gray
6	O_D5	Data output				pink
7	O_D6	Data output				blue
8	O_D7	Data output				red
9	O_D8	Data output				black
10	not connected					
11	not connected					
12	not connected					
13	not connected					
14	not connected					
15	not connected					
16	Parity_Odd_OUT	Parity Odd				yellow/brown
17	Parity_Even_OUT	Parity Even				withe/gray
18	not connected					
19	not connected					
20	not connected					
21	Direction IN	Change of counting direction	Supply Voltage		0	withe/blue
22	not connected					
23	not connected					
24	Supply Voltage IN	Supply voltage	11-27V			brown/red
25	Ground IN	Ground	0V			withe/black

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.

Pin assignment

Pin assignment number: 1074

Index: + 2050 = K140

20.07.2011

Connector name: 25-pol.HARTING Pin-count: 25

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
A1	O_D0	Data output				white
A2	O_D1	Data output				brown
A3	O_D2	Data output				green
A4	O_D3	Data output				yellow
A5	O_D4	Data output				gray
A6	O_D5	Data output				pink
A7	not connected					
A8	Ground IN	Ground	0V			red
A9	Ground IN	Ground	0V			black
B2	O_D6	Data output				violet
B3	O_D7	Data output				gray/pink
B4	O_D8	Data output				red/blue
B5	not connected					
B6	not connected					
B7	not connected					
B8	Parity_Odd_OUT	Parity Odd				yellow/brown
C1	not connected					
C2	Parity_Even_OUT	Parity Even				gray/brown
C3	Direction IN	Change of counting direction	Supply Voltage		0	white/pink
C4	Supply Voltage IN	Supply voltage	11-27V			pink/brown
C5	not connected					
C6	not connected					
C7	not connected					
C8	not connected					
C9	not connected					

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!

Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.