

Pin assignment

Pin assignment number: 2644

Index: + 1848 = K194

26.07.2011

Connector name: 8-pol.HARTING Pin-count: 8

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	CH_A_OUT	Channel A	5V	RS 422		brown
2	/CH_A_OUT	Channel A inverted	5V	RS 422		green
3	CH_B_OUT	Channel B	5V	RS 422		gray
4	/CH_B_OUT	Channel B inverted	5V	RS 422		pink
5	CH_I_OUT	Channel Reference	5V	RS 422		red
6	/CH_I_OUT	Channel Reference inverted	5V	RS 422		black
7	Supply Voltage IN	Supply voltage	11-27V			brown 0,5
8	Ground IN	Ground	0V			withe 0,5

Notice 8p.Harting :

'!!!! 8 pole Harting " Socket " !!!!!

Pin assignment

Pin assignment number: 1848

Index: + 2644 = K194

26.07.2011

Connector name: 8-pol.HARTING Pin-count: 8

Page: 1/1

Pin	Designation	Description	Level	Driver	NC	Color
1	not connected					
2	not connected					
3	HAS_Data+_OUT	Data output +	RS 422	RS 422		green
4	HAS_Data-_OUT	Data output -	RS 422	RS 422		yellow
5	not connected					
6	not connected					
7	Supply Voltage IN	Supply voltage	11-27V			blue
8	Ground IN	Ground	0V			red

WARNING !!

'De-energize the system before carrying out wiring work or opening and closing electrical connections !!!
Short-circuits, voltage peaks, etc. can cause operating failures and uncontrolled operating states, as well as serious personal injuries and damage to property.

Verdrahtungsarbeiten, Öffnen und Schließen von elektrischen Verbindungen nur im spannungslosen Zustand durchführen !!! Kurzschlüsse, Spannungsspitzen etc. können zur Fehlfunktion und unkontrollierten Zuständen der Anlage bzw. zu erheblichen Personen- und Sachschäden führen.